

HT90**Non-contact Voltage Detector**

Function	
Display	LED
Range of voltage detection	high sensitivity: AC12~1000V; Low sensitivity: AC48~1000V
frequency	50/60Hz
Alarm mode	Sound and light alarm
Probe shape	Prolate shape
Live and Neutral	According Signal strength indication , the test signal on the fire line is stronger than Neutral's
Signal Intensity display	Three level sensitivity of LED
Signal Intensity Indication method	sound from slow to fast; LED from low to high
Flashlight	✓
Auto power off	No operation, no sensing signal will shut down automatically in about 5 minutes.
Low-battery Indication	✓
Power Supply	2x1.5V AAA batteries
Weight	Approx.30 g
Size	145mmx28mmx24mm
Safety rating	EN61010-1,-2-030; EN61326-1, CAT III 1000V

**HT100****Non-contact Voltage/ Phase Detector****NEW**

Specifications	Function
Display	Bar graph
Range of voltage detection	high sensitivity: AC12~1000V; Low sensitivity: AC48~1000V
frequency	50/60Hz
Alarm mode	Sound and light alarm
Probe shape	Prolate shape
Backlight	Red and green double color backlight
Live and Neutral	According to backlight color change: green is neutral wire; red is live wire.
Signal intensity display	Four level sensitivity of bar graph
Signal intensity indication method	sound from slow to fast; backlight from green to red; bar graph from low to high
Flashlight	No operation, no sensing signal will shut down automatically in about 3 minutes.
Auto power off	No operation, no sensing signal will shut down automatically in about 3 minutes.
Low-battery indication	✓
Power Supply	2x1.5V AAA batteries
Weight	Approx. 32g
Size	157mm x 27mm x 23mm
Safety rating	EN61010-1,-2-030; EN61326-1, CAT III 1000V

